

## Dimmerkompatibilitätsliste

### Leuchtmittel (LO-COB12-5WDIM, LO-COB230-5WDIM, LO-COB230-8WDIM)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-COB12-5WDIM		LO-COB230-5WDIM	LO-COB230-8WDIM	
ABB STD 50-3 L	X	100-8%	99-2%	85-0%	87-0%
Altenburger 50,3	71-1%	100-12%	99-0%	92-0%	92-0%
Aurora DSP400 L	X	X	99-0%	89-0%	89-0%
Berker 2861U	75-0%	100-6%	99-0%	88-0%	88-0%
Bticino L/N/NT4411N	X	100-8%	100-0%	93-0%	92-0%
Bticino NT4402N R	X	100-31%	X	X	X
Busch & Jäger 6513 U-102 T	78-8%	98-22%	100-0%	X	X
Busch & Jäger 6523 U-102 T	67-3%	100-11%	100-9%	94-3%	93-3%
Busch & Jäger 2250U L	56-1%	100-1%	X	90-1%	87-1%
Busch & Jäger 6526U	X	X	99-20%	X	X
Century Control Multi Dimmer U	78-0%	99-0%	99-0%	90-0%	90-0%
DimMax 420SL L/T	X	X	X	92-0%	91-0%
Dinuy RE EL1 LE1 LED	80-0%	100-1%	X	91-0%	91-0%

## Dimmerkompatibilitätsliste

### Leuchtmittel (LO-COB12-5WDIM, LO-COB230-5WDIM, LO-COB230-8WDIM)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-COB12-5WDIM		LO-COB230-5WDIM	LO-COB230-8WDIM	
Domintell DimMax 420SL L/T	X	X	100-0%	92-0%	91-0%
Elko 400GLI	X	X	100-0%	92-3%	90-0%
Elko 315GLE T	76-4%	100-14%	100-0%	91-3%	90-0%
Elko 600GLE/I	72-5%	100-5%	99-1%	91-0%	91-0%
Elko 600GLi U	78-22%	99-18%	99-0%	91-2%	91-2%
Elko 420GLE/I U	X	99-13%	100-0%	X	X
Elko 1000LRI	X	99-0%	99-0%	87-0%	87-0%
Elko 630GLE U	72-1%	99-12%	100-7%	92-1%	92-1%
Eltako EUD61NPN-UC R/L/C	82-13%	100-27%	100-0%	89-1%	88-1%
Feller 40200.LEDxxx	X	X	100-1%	94-0%	93-0%
Feller 40600RLC U	72-5%	100-5%	99-1%	91-0%	91-0%
Feller 40600.RC	72-1%	99-12%	100-7%	92-1%	92-1%
Feller 40600.RL	78-22%	99-18%	99-0%	91-2%	91-2%

## Dimmerkompatibilitätsliste

### Leuchtmittel (LO-COB12-5WDIM, LO-COB230-5WDIM, LO-COB230-8WDIM)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-COB12-5WDIM		LO-COB230-5WDIM	LO-COB230-8WDIM	
Feller 40420.RLC	X	99-13%	100-0%	X	X
Feller 31000	X	99-0%	99-0%	87-0%	87-0%
Gira 226200	56-1%	99-12%	100-0%	90-0%	89-0%
Gira 030700 T	69-8%	100-19%	100-0%	89-0%	89-0%
Gira 117600 U	75-0%	100-16%	100-7%	X	X
Gira 238500	X	X	X	X	X
Gira 217400 KNX-U	78-0%	100-16%	99-41%	90-29%	90-27%
Hager WUD87 LED-U	62-1%	100-12%	100-0%	92-0%	91-0%
Hamilton KP1X40	X	100-5%	X	X	X
Hugo Müller paladin 872110 led	80-0%	100-1%	X	91-0%	91-0%
Jung 225 NVDE L	56-1%	99-12%	100-0%	90-0%	89-0%
Jung 225 TDE	69-8%	100-19%	100-0%	89-0%	89-0%
Jung 254 UDIE1	75-0%	100-16%	100-7%	X	X

## Dimmerkompatibilitätsliste

### Leuchtmittel (LO-COB12-5WDIM, LO-COB230-5WDIM, LO-COB230-8WDIM)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-COB12-5WDIM		LO-COB230-5WDIM	LO-COB230-8WDIM	
Jung 1224 LEDUDE LED	X	X	X	X	91-6%
Jung 3904 REGHE	78-0%	100-16%	99-41%	90-29%	90-27%
Legrand 665114 U	X	100-8%	100-0%	93-0%	92-0%
Legrand 574319/574339 U	X	100-8%	100-0%	93-0%	92-0%
Legrand 572239/572739 U	X	100-8%	100-0%	93-0%	92-0%
Legrand 078407/079207 U	X	100-8%	100-0%	93-0%	92-0%
Legrand 048869/048871 U	X	100-8%	100-0%	93-0%	92-0%
Legrand 067083/048869 U	X	100-8%	100-0%	93-0%	92-0%
Legrand 770061	X	X	100-0%	X	X
Legrand 099314 RL	X	100-10%	100-0%	66-2%	X
Legrand 770062 RLC	69-0%	97-2%	100-0%	82-1%	86-1%
Master DM-DGL U/LED	76-0%	99-0%	X	X	X
Master DM-2500 U/LED	X	99-0%	99-0%	X	X

## Dimmerkompatibilitätsliste

### Leuchtmittel (LO-COB12-5WDIM, LO-COB230-5WDIM, LO-COB230-8WDIM)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-COB12-5WDIM		LO-COB230-5WDIM	LO-COB230-8WDIM	
Merten MEG5136-0000	76-4%	100-14%	100-0%	91-3%	90-0%
Merten MEG5134-0000	X	X	100-1%	94-0%	93-0%
Merten MEG5139-0000	72-5%	100-5%	99-1%	91-0%	91-0%
Merten MEG5137-0000	72-1%	99-12%	100-7%	92-1%	92-1%
Merten MEG5133-0000	78-22%	99-18%	99-0%	91-2%	91-2%
Merten MEG5138-0000	X	99-13%	100-0%	X	X
Merten MEG5170-0300 U	X	100-11%	100-0%	90-0%	89-0%
Merten MEG 5131 L	82-14%	100-14%	99-0%	94-0%	94-0%
Merten MEG 5132	82-14%	100-14%	99-0%	94-0%	94-0%
Merten MEG 5140 L	78-10%	99-21%	99-0%	92-0%	91-0%
Merten MEG 5135 L	X	99-0%	99-0%	87-0%	87-0%
MK K4501 L	80-13%	100-8%	99-0%	88-1%	87-7%
Nexus 881P-01 L	64-1%	X	100-0%	92-1%	92-1%

## Dimmerkompatibilitätsliste

### Leuchtmittel (LO-COB12-5WDIM, LO-COB230-5WDIM, LO-COB230-8WDIM)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-COB12-5WDIM		LO-COB230-5WDIM	LO-COB230-8WDIM	
	Spalte1	Spalte2		Spalte1	Spalte2
Niko 310-01900 U	82-0%	100-2%	99-0%	94-0%	93-0%
Niko 330-00700 U	82-7%	100-16%	99-0%	92-0%	92-0%
Odace S520512	X	X	100-1%	94-0%	93-0%
Odace S520511	78-22%	99-18%	99-0%	91-2%	91-2%
Odace S520515	X	99-13%	100-0%	X	X
Odace S520518	78-10%	99-21%	99-0%	92-0%	91-0%
Osram HTi DALI 315 DIM DALI-T	82-3%	100-10%	100-0%	94-0%	94-0%
Peha 435 HAN L	69-1%	X	100-2%	91-0%	91-0%
Schneider 400GLI T	X	X	100-0%	92-3%	90-0%
Schneider SBD315RC	76-4%	100-14%	100-0%	91-3%	90-0%
Schneider SBD200LED	X	X	100-1%	94-0%	93-0%
Schneider SBD600RCRL	72-5%	100-5%	99-1%	91-0%	91-0%
Schneider SBD630RC	72-1%	99-12%	100-7%	92-1%	92-1%

## Dimmerkompatibilitätsliste

### Leuchtmittel (LO-COB12-5WDIM, LO-COB230-5WDIM, LO-COB230-8WDIM)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-COB12-5WDIM		LO-COB230-5WDIM	LO-COB230-8WDIM	
Schneider 600RL	78-22%	99-18%	99-0%	91-2%	91-2%
Schneider SBD420RCRL	X	99-13%	100-0%	X	X
Schneider 5170	X	100-11%	100-0%	90-0%	89-0%
Schneider SBD400RL	82-14%	100-14%	99-0%	94-0%	94-0%
Schneider SBDSPL	78-10%	99-21%	99-0%	92-0%	91-0%
Schneider ATTD1000RL	X	99-0%	99-0%	87-0%	87-0%
Shuttle SDIM-T-LED-500W T & LED-T	78-3%	100-3%	100-0%	92-0%	92-0%
Siemens 5TC8 284 T	67-3%	99-14%	100-3%	87-0%	87-0%
Siemens 5WG1-527-1AB31 KNX-U	82-0%	100-0%	99-0%	85-0%	84-0%
Vadsbo LD220 U	79-3%	100-0%	100-0%	89-1%	89-1%
Vari Light HQ3W	62-9%	X	100-0%	65-0%	65-0%
Vari Light JQP401W T	X	99-6%	X	X	87-3%
Vimar 20135 U	80-10%	100-24%	100-0%	85-1%	85-1%

## Dimmerkompatibilitätsliste

### Leuchtmittel (LO-COB12-5WDIM, LO-COB230-5WDIM, LO-COB230-8WDIM)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-COB12-5WDIM		LO-COB230-5WDIM	LO-COB230-8WDIM	
	X	X			
Zano WH401 L	X	X	100-0%	99-3%	60-3%
Zano WH251	X	X	X	X	53-0%
Zano Z GRID 700 LED	52-0%	100-0%	X	X	X
Zano Z GRID 500	57-1%	100-0%	X	89-0%	89-0%