

Dimmerkompatibilitätsliste

Leuchtmittel (LO-R7s78-8WD-SWW, LO-R7s118-15WD-SWW, LO-COBG53-12WDIM, LO-GLOWGU10-6WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-R7s78-8WD-SWW		LO-R7s118-15WD-SWW		LO-COBG53-12WDIM		LO-GLOWGU10-6WD	
ABB STD 50-3 L	100-8%	100-12%	100-15%	100-7%	61-2%	X	96-6%	96-5%
Altenburger 50,3	X	X	100-13%	100-1%	82-0%	X	98-10%	95-6%
Aurora DSP400 L	X	88-0%	X	X	54-0%	100-0%	X	X
Aurora DSP400 T	X	X	X	X	X	X	93-2%	94-2%
Berker 2861U	100-12%	100-12%	100-13%	100-10%	90-0%	100-3%	99-2%	97-2%
Bticino L/N/NT4411N	100-0%	100-0%	100-13%	100-4%	92-4%	100-0%	88-8%	90-8%
Bticino L/N/NT4408	100-0%	X	100-0%	100-0%	X	X	X	X
Bticino NT4402N R	X	X	100-22%	100-18%	X	X	X	X
Busch & Jäger 6513 U-102 T	100-28%	X	X	X	92-21%	X	86-3%	88-4%
Busch & Jäger 6523 U-102 T	100-44%	X	97-0%	100-0%	X	88-31%	80-4%	86-4%
Busch & Jäger 2250U L	X	X	100-0%	X	64-0%	X	X	X
Century Control Multi Dimmer U	100-0%	X	100-0%	100-0%	91-0%	100-0%	93-55	94-3%
DimMax 420SL L/T	100-0%	100-0%	100-0%	100-0%	94-0%	100-0%	99-5%	96-2%

Dimmerkompatibilitätsliste

Leuchtmittel (LO-R7s78-8WD-SWW, LO-R7s118-15WD-SWW, LO-COBG53-12WDIM, LO-GLOWGU10-6WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-R7s78-8WD-SWW		LO-R7s118-15WD-SWW		LO-COBG53-12WDIM		LO-GLOWGU10-6WD	
Dinuy RE EL1 LE1 LED	100-0%	100-0%	98-0%	100-0%	92-0%	100-0%	100-12%	99-14%
Elko 400GLI	60-0%	72-0%	100-0%	100-0%	X	99-0%	85-8%	91-8%
Elko 315GLE T	100-0%	100-0%	100-0%	100-0%	85-0%	94-0%	94-8%	94-8%
Elko 600GLE/I	100-0%	X	100-0%	100-7%	93-0%	100-0%	92-2%	92-0%
Elko 600GLi U	100-0%	92-0%	100-0%	100-0%	91-7%	100-0%	99-8%	97-2%
Elko 420GLE/I U	X	100-8%	100-4%	100-4%	92-2%	100-0%	94-4%	92-4%
Elko 1000LRI	100-100%	100-100%	X	X	X	100-0%	100-1%	100-0%
Elko 630GLE U	100-20%	100-12%	97-16%	100-7%	84-6%	99-8%	99-8%	97-2%
Eltako EUD61NPN-UC R/L/C	100-0%	100-0%	100-0%	100-0%	87-0%	100-0%	100-1%	100-0%
Feller 40200.LEDxxx	100-0%	X	100-6%	100-3%	83-0%	96-0%	98-8%	96-3%
Feller 40600RLC U	100-0%	X	100-0%	100-7%	93-0%	100-0%	92-2%	92-0%
Feller 40600.RC	100-20%	100-12%	97-16%	100-7%	84-6%	99-8%	99-8%	97-2%
Feller 40600.RL	100-0%	92-0%	100-0%	100-0%	91-7%	100-0%	99-8%	97-2%

Dimmerkompatibilitätsliste

Leuchtmittel (LO-R7s78-8WD-SWW, LO-R7s118-15WD-SWW, LO-COBG53-12WDIM, LO-GLOWGU10-6WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-R7s78-8WD-SWW		LO-R7s118-15WD-SWW		LO-COBG53-12WDIM		LO-GLOWGU10-6WD	
Feller 40420.RLC	X	100-8%	100-4%	100-4%	92-2%	100-0%	94-4%	92-4%
Feller 31000	100-100%	100-100%	X	X	X	100-0%	100-1%	100-0%
Gira 226200	X	X	100-15%	100-4%	80-0%	99-0%	92-10%	92-10%
Gira 030700 T	100-12%	100-8%	100-15%	100-4%	89-9%	X	95-12%	96-11%
Gira 117600 U	X	X	X	X	89-0%	100-8%	99-2%	97-0%
Gira 238500	100-0%	100-0%	X	X	X	X	X	X
Gira 217400 KNX-U	100-0%	100-12%	100-14%	100-3%	92-5%	X	96-3%	95-3%
Hager WUD87 LED-U	100-12%	100-12%	99-15%	99-15%	94-0%	X	96-3%	93-3%
Hamilton KP1X40	X	X	X	X	X	X	86-3%	87-1%
Hugo Müller paladin 872110 led	100-0%	1000-0%	98-0%	100-0%	92-0%	100-0%	100-12%	99-14%
Jung 225 NVDE L	X	X	100-15%	100-4%	61-0%	100-0%	92-10%	92-10%
Jung 225 TDE	100-12%	100-8%	100-15%	100-4%	89-9%	X	95-12%	96-11%
Jung 254 UDIE1	X	X	X	X	89-0%	100-8%	99-2%	97-0%

Dimmerkompatibilitätsliste

Leuchtmittel (LO-R7s78-8WD-SWW, LO-R7s118-15WD-SWW, LO-COBG53-12WDIM, LO-GLOWGU10-6WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-R7s78-8WD-SWW		LO-R7s118-15WD-SWW		LO-COBG53-12WDIM		LO-GLOWGU10-6WD	
Jung 1224 LEDUCE LED	100-0%	100-0%	X	X	74-0%	96-0%	99-4%	98-4%
Jung 3904 REGHE	100-0%	100-12%	100-14%	100-3%	92-5%	X	96-3%	95-3%
Legrand 665114 U	100-0%	100-0%	100-13%	100-4%	92-4%	100-0%	88-8%	90-8%
Legrand 574319/574339 U	100-0%	100-0%	100-13%	100-4%	92-4%	100-0%	88-8%	90-8%
Legrand 572239/572739 U	100-0%	100-0%	100-13%	100-4%	92-4%	100-0%	88-8%	90-8%
Legrand 078407/079207 U	100-0%	100-0%	100-13%	100-4%	92-4%	100-0%	88-8%	90-8%
Legrand 048869/048871 U	100-0%	100-0%	100-13%	100-4%	92-4%	100-0%	88-8%	90-8%
Legrand 067083/048869	100-0%	100-0%	100-13%	100-4%	92-4%	100-0%	88-8%	90-8%
Legrand 099314 RL	X	100-100%	X	X	85-0%	95-0%	X	96-0%
Legrand 770062 RLC	100-0%	100-0%	100-0%	100-0%	84-0%	94-0%	X	X
Legrand 078405 RL	100-0%	X	100-0%	100-0%	X	X	X	X
Legrand 752162 T	X	X	X	X	X	X	X	96-0%
Master DM-DGL U/LED	X	X	X	X	X	X	100-11%	100-9%

Dimmerkompatibilitätsliste

Leuchtmittel (LO-R7s78-8WD-SWW, LO-R7s118-15WD-SWW, LO-COBG53-12WDIM, LO-GLOWGU10-6WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-R7s78-8WD-SWW		LO-R7s118-15WD-SWW		LO-COBG53-12WDIM		LO-GLOWGU10-6WD	
Master DM-2500 U/LED	100-0%	100-0%	100-0%	X	93-0%	X	X	X
Merten MEG5136-0000	100-0%	100-0%	100-0%	100-0%	85-0%	94-0%	94-8%	94-8%
Merten MEG5134-0000	100-0%	X	100-6%	100-3%	83-0%	96-0%	98-8%	96-3%
Merten MEG5139-0000	100-0%	X	100-0%	100-7%	93-0%	100-0%	92-2%	92-0%
Merten MEG5137-0000	100-20%	100-12%	97-16%	100-7%	84-6%	99-8%	99-8%	97-2%
Merten MEG5133-0000	100-0%	92-0%	100-0%	100-0%	91-7%	100-0%	99-8%	97-2%
Merten MEG5138-0000	X	100-8%	100-4%	100-4%	92-2%	100-0%	94-4%	92-4%
Merten MEG5170-0300 U	64-8%	64-8%	X	X	81-0%	92-0%	X	X
Merten MEG 5131 L	100-0%	100-0%	100-0%	100-0%	92-0%	X	93-2%	93-4%
Merten MEG 5132	100-0%	100-0%	100-0%	100-0%	92-0%	X	93-2%	93-4%
Merten MEG 5140 L	X	X	100-0%	100-0%	X	X	90-5%	91-5%
Merten MEG 5135 L	100-100%	100-100%	X	X	X	100-0%	100-1%	100-0%
MK K4501 L	100-0%	100-12%	100-0%	100-3%	80-0%	91-0%	92-5%	93-2%

Dimmerkompatibilitätsliste

Leuchtmittel (LO-R7s78-8WD-SWW, LO-R7s118-15WD-SWW, LO-COBG53-12WDIM, LO-GLOWGU10-6WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-R7s78-8WD-SWW		LO-R7s118-15WD-SWW		LO-COBG53-12WDIM		LO-GLOWGU10-6WD	
Nexus 881P-01 L	100-0%	X	X	100-0%	66-0%	100-0%	93-2%	97-1%
Niko 310-0190001901 U	100-0%	100-0%	100-0%	100-0%	93-0%	100-0%	100-2%	100-2%
Niko 330-0070000701 U	100-8%	100-8%	100-2%	100-2%	94-0%	X	100-6%	100-5%
Odace S520512	100-0%	X	100-6%	100-3%	83-0%	96-0%	98-8%	96-3%
Odace S520511	100-0%	92-0%	100-0%	100-0%	91-7%	100-0%	99-8%	97-2%
Odace S520515	X	100-8%	100-4%	100-4%	92-2%	100-0%	94-4%	92-4%
Odace S520518	X	X	100-0%	100-0%	X	X	90-5%	91-5%
Osram HTi DALI 315 DIM DALI-T	100-0%	X	100-0%	100-3%	95-1%	100-0%	X	X
Peha 435 HAN L	60-4%	72-8%	86-0%	100-1%	X	91-0%	90-7%	91-5%
Schneider 400GLI T	60-0%	72-0%	100-0%	100-0%	X	99-0%	85-8%	91-8%
Schneider SBD315RC	100-0%	100-0%	100-0%	100-0%	85-0%	94-0%	94-8%	94-8%
Schneider SBD200LED	100-0%	X	100-6%	100-3%	83-0%	96-0%	98-8%	96-3%
Schneider SBD600RCRL	100-0%	X	100-0%	100-7%	93-0%	100-0%	92-2%	92-0%

Dimmerkompatibilitätsliste

Leuchtmittel (LO-R7s78-8WD-SWW, LO-R7s118-15WD-SWW, LO-COBG53-12WDIM, LO-GLOWGU10-6WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-R7s78-8WD-SWW		LO-R7s118-15WD-SWW		LO-COBG53-12WDIM		LO-GLOWGU10-6WD	
Schneider SBD630RC	100-20%	100-12%	97-16%	100-7%	84-6%	99-8%	99-8%	97-2%
Schneider 600RL	100-0%	92-0%	100-0%	100-0%	91-7%	100-0%	99-8%	97-2%
Schneider SBD420RCRL	X	100-8%	100-4%	100-4%	92-2%	100-0%	94-4%	92-4%
Schneider 5170	64-8%	64-8%	X	X	81-0%	92-0%	X	X
Schneider SBD400RL	100-0%	100-0%	100-0%	100-0%	92-0%	X	93-2%	93-4%
Schneider SBDSPL	X	X	100-0%	100-0%	X	X	90-5%	91-5%
Schneider ATTD1000RL	100-100%	100-100%	X	X	X	100-0%	100-1%	100-0%
Shuttle SDIM-T-LED-500W T & LED-T	100-0%	100-0%	100-0%	100-0%	88-0%	X	96-9%	932-10%
Siemens 5TC8 284 T	X	X	100-13%	100-4%	83-9%	92-0%	92-14%	92-13%
Siemens 5WG1-527-1AB31 KNX-U	100-100%	100-100%	100-0%	100-0%	92-0%	100-0%	97-11%	95-3%
theben DIMAX 544 plus P T	100-12%	100-0%	100-8%	100-6%	93-7%	100-1%	X	X
theben DIMAX 534 plus T	100-8%	100-8%	100-0%	100-0%	92-6%	X	X	X
Vadsbo LD220 U	100-0%	X	100-0%	X	X	100-0%	92-2%	96-4%

Dimmerkompatibilitätsliste

Leuchtmittel (LO-R7s78-8WD-SWW, LO-R7s118-15WD-SWW, LO-COBG53-12WDIM, LO-GLOWGU10-6WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-R7s78-8WD-SWW		LO-R7s118-15WD-SWW		LO-COBG53-12WDIM		LO-GLOWGU10-6WD	
Vari Light HQ3W	100-0%	X	100-0%	100-0%	81-0%	89-0%	96-4%	97-1%
Vari Light JQP401W T	X	100-12%	99-0%	X	67-0%	100-0%	100-11%	98-10%
Vimar 20135 U	100-0%	100-0%	100-0%	100-0%	89-0%	100-0%	98-0%	98-0%
Zano WH401 L	100-0%	100-0%	100-0%	X	66-0%	100-0%	97-2%	97-3%
Zano WH251	100-0%	100-0%	100-0%	X	64-0%	100-0%	99-3%	99-1%
Zano Z GRID 700 LED	X	X	X	X	X	X	91-4%	88-3%
Zano Z GRID 500	X	100-0%	X	100-0%	X	100-0%	96-3%	96-1%