

Dimmerkompatibilitätsliste

Leuchtmittel (LO-FROAGL-5WD, LO-FROAGL-7WD, LO-FROAGL-9WD, LO-FROAGL-12WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-FROAGL-5WD		LO-FROAGL-7WD		LO-FROAGL-9WD		LO-FROAGL-12WD	
	Spalte1	Spalte2	Spalte1	Spalte2	Spalte1	Spalte2	Spalte1	Spalte2
ABB STD 50-3 L	77-0%	97-0%	91-0%	100-1%	95-18%	93-19%	100-14%	100-17%
Altenburger 50,3	95-0%	85-0%	88-0%	X	92-19%	X	98-22%	95-16%
Aurora DSP400 L	74-0%	91-0%	91-0%	98-0%	X	91-0%	100-0%	100-0%
Berker 2861U	97-0%	85-0%	X	X	X	X	95-34%	98-31%
Bticino L/N/NT4411N	X	X	79-0%	93-0%	92-5%	94-0%	99-9%	98-11%
Bticino L/N/NT4408	X	87-0%	X	X	X	X	100-0%	99-0%
Bticino NT4402N R	X	95-0%	X	X	89-20%	89-21%	73-15%	X
Busch & Jäger 6513 U-102 T	98-0%	99-0%	93-0%	94-0%	93-26%	90-16%	99-27%	99-23%
Busch & Jäger 6523 U-102 T	97-0%	98-0%	70-0%	72-0%	89-0%	92-14%	100-44%	X
Busch & Jäger 2250U L	X	X	X	92-0%	86-0%	95-0%	100-0%	100-0%
Busch & Jäger 6526U	97-0%	79-0%	X	X	X	X	X	X
Century Control Multi Dimmer U	82-0%	98-0%	88-0%	98-0%	91-1%	95-0%	98-2%	100-5%
DimMax 420SL L/T	92-0%	84-0%	91-0%	93-0%	100-2%	99-2%	98-10%	100-10%

Dimmerkompatibilitätsliste

Leuchtmittel (LO-FROAGL-5WD, LO-FROAGL-7WD, LO-FROAGL-9WD, LO-FROAGL-12WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-FROAGL-5WD		LO-FROAGL-7WD		LO-FROAGL-9WD		LO-FROAGL-12WD	
	Spalte1	Spalte2	Spalte1	Spalte2	Spalte1	Spalte2	Spalte1	Spalte2
Dinuy RE EL1 LE1 LED	85-0%	85-0%	93-1%	99-1%	99-24%	97-23%	100-11%	99-10%
Elko 400GLI	X	X	69-0%	69-0%	X	88-4%	100-0%	100-0%
Elko 315GLE T	92-0%	97-0%	X	X	X	X	99-8%	98-7%
Elko 600GLE/I	X	98-0%	85-0%	75-0%	91-0%	93-15%	100-12%	100-14%
Elko 600GLi U	92-0%	91-0%	79-0%	78-0%	90-0%	91-8%	100-12%	100-11%
Elko 420GLE/I U	78-0%	98-0%	88-0%	X	96-5%	93-5%	100-10%	100-9%
Elko 1000LRI	96-0%	91-0%	90-0%	99-0%	99-0%	98-0%	100-101%	100-101%
Elko 630GLE U	95-0%	92-0%	X	X	93-19%	88-13%	99-29%	100-24%
Eltako EUD61NPN-UC R/L/C	85-0%	85-0%	94-0%	99-0%	88-0%	87-0%	97-6%	97-5%
Feller 40200.LEDxxx	98-0%	96-0%	X	X	89-14%	85-10%	96-26%	99-24%
Feller 40600RLC U	X	98-0%	85-0%	75-0%	91-0%	93-15%	100-12%	100-14%
Feller 40600.RC	95-0%	92-0%	X	X	93-19%	88-13%	99-29%	100-24%
Feller 40600.RL	92-0%	91-0%	79-0%	78-0%	90-0%	91-8%	100-12%	100-11%

Dimmerkompatibilitätsliste

Leuchtmittel (LO-FROAGL-5WD, LO-FROAGL-7WD, LO-FROAGL-9WD, LO-FROAGL-12WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-FROAGL-5WD		LO-FROAGL-7WD		LO-FROAGL-9WD		LO-FROAGL-12WD	
	Spalte1	Spalte2	Spalte1	Spalte2	Spalte1	Spalte2	Spalte1	Spalte2
Feller 40420.RLC	89-0%	98-0%	88-0%	X	96-5%	93-5%	100-10%	100-9%
Feller 31000	96-0%	91-0%	90-0%	99-0%	99-0%	98-0%	100-101%	100-101%
Gira 226200	85-0%	97-0%	79-0%	83-0%	92-14%	94-3%	98-0%	100-0%
Gira 030700 T	98-0%	96-0%	93-0%	94-0%	92-19%	87-11%	98-27%	98-22%
Gira 117600 U	100-0%	97-0%	X	X	X	X	98-33%	99-31%
Gira 238500	99-0%	99-0%	X	X	X	X	99-5%	99-6%
Gira 217400 KNX-U	81-0%	83-0%	93-0%	99-19%	97-16%	93-10%	98-0%	98-0%
Hager WUD87 LED-U	77-0%	82-0%	88-0%	X	87-18%	89-12%	97-23%	96-18%
Hamilton KP1X40	74-0%	96-0%	92-0%	X	X	X	X	X
Hugo Müller paladin 872110 led	X	X	93-1%	99-1%	99-24%	97-23%	100-11%	99-10%
Jung 225 NVDE L	85-0%	97-0%	79-0%	83-0%	92-14%	94-3%	98-0%	100-0%
Jung 225 TDE	98-0%	96-0%	93-0%	94-0%	92-19%	87-11%	98-27%	98-22%
Jung 254 UDIE1	100-0%	97-0%	X	X	X	X	98-33%	99-31%

Dimmerkompatibilitätsliste

Leuchtmittel (LO-FROAGL-5WD, LO-FROAGL-7WD, LO-FROAGL-9WD, LO-FROAGL-12WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-FROAGL-5WD		LO-FROAGL-7WD		LO-FROAGL-9WD		LO-FROAGL-12WD	
Jung 1224 LEDUDE LED	99-0%	99-0%	X	X	X	X	99-5%	99-6%
Jung 3904 REGHE	X	X	X	X	97-16%	93-10%	98-0%	98-0%
Legrand 665114 U	X	X	79-0%	83-0%	92-5%	94-0%	99-9%	98-11%
Legrand 574319/574339 U	X	X	79-0%	83-0%	92-5%	94-0%	99-9%	98-11%
Legrand 572239/572739 U	X	X	79-0%	83-0%	92-5%	94-0%	99-9%	98-11%
Legrand 078407/079207 U	X	X	79-0%	83-0%	92-5%	94-0%	99-9%	98-11%
Legrand 048869/048871 U	X	X	79-0%	83-0%	92-5%	94-0%	99-9%	98-11%
Legrand 067083/048869 U	X	X	79-0%	83-0%	92-5%	94-0%	99-9%	98-11%
Legrand 770061	82-0%	X	X	X	X	X	X	X
Legrand 099314 RL	74-0%	85-0%	X	X	X	X	98-5%	X
Legrand 770062 RLC	X	100-0%	83-0%	100-0%	83-0%	83-0%	X	98-5%
Legrand 078405 RL	75-0%	87-0%	X	X	X	X	100-0%	99-0%
Master DM-DGL U/LED	77-0%	85-0%	88-30%	99-43%	X	X	X	X

Dimmerkompatibilitätsliste

Leuchtmittel (LO-FROAGL-5WD, LO-FROAGL-7WD, LO-FROAGL-9WD, LO-FROAGL-12WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-FROAGL-5WD		LO-FROAGL-7WD		LO-FROAGL-9WD		LO-FROAGL-12WD	
	Spalte1	Spalte2	Spalte1	Spalte2	Spalte1	Spalte2	Spalte1	Spalte2
Master DM-2500 U/LED								
Merten MEG5136-0000	X		X	X	X	X		
Merten MEG5134-0000			X	X	89-14%	85-10%	96-26%	99-24%
Merten MEG5139-0000	X		85-0%	75-0%	91-0%	93-15%	100-12%	100-14%
Merten MEG5137-0000			X	X	93-19%	88-13%	99-29%	100-24%
Merten MEG5133-0000			79-0%	78-0%	90-0%	91-8%	100-12%	100-11%
Merten MEG5138-0000			88-0%	X	96-5%	93-5%	100-10%	100-9%
Merten MEG5170-0300 U			89-0%	X	85-15%	X	91-34%	88-31%
Merten MEG 5131 L			69-0%	75-0%	91-0%	94-0%	100-0%	100-0%
Merten MEG 5132			69-0%	75-0%	91-0%	94-0%	100-0%	100-0%
Merten MEG 5140 L			67-0%	78-0%	83-0%	86-0%	88-0%	99-0%
Merten MEG 5135 L			90-0%	99-0%	99-0%	98-0%	100-101%	100-101%
MK K4501 L	X		94-0%	100-0%	80-3%	86-7%	100-11%	100-13%

Dimmerkompatibilitätsliste

Leuchtmittel (LO-FROAGL-5WD, LO-FROAGL-7WD, LO-FROAGL-9WD, LO-FROAGL-12WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-FROAGL-5WD		LO-FROAGL-7WD		LO-FROAGL-9WD		LO-FROAGL-12WD	
	Spalte1	Spalte2	Spalte1	Spalte2	Spalte1	Spalte2	Spalte1	Spalte2
Nexus 881P-01 L	69-0%	98-0%	82-0%	96-0%	79-0%	97-0%	98-0%	99-0%
Niko 310-01900 U	85-0%	85-0%	94-0%	100-0%	100-0%	97-0%	100-5%	100-5%
Niko 330-00700 U	65-0%	85-0%	93-1%	100-2%	95-32%	93-26%	100-15%	100-14%
Odace S520512	98-0%	96-0%	X	X	89-14%	85-10%	96-26%	99-24%
Odace S520511	92-0%	91-0%	79-0%	78-0%	90-0%	91-8%	100-12%	100-11%
Odace S520515	89-0%	98-0%	88-0%	X	96-5%	93-5%	100-10%	100-9%
Odace S520518	58-0%	82-0%	67-0%	78-0%	83-0%	86-0%	88-0%	99-0%
Osram HTi DALI 315 DIM DALI-T	X	100-0%	94-0%	94-0%	X	97-6%	100-17%	100-16%
Peha 435 HAN L	X	81-0%	66-0%	78-0%	82-4%	84-2%	98-18%	100-18%
Schneider 400GLI T	X	X	69-0%	69-0%	X	88-4%	100-0%	100-0%
Schneider SBD315RC	X	97-0%	X	X	X	X	99-8%	98-7%
Schneider SBD200LED	98-0%	96-0%	X	X	89-14%	85-10%	96-26%	99-24%
Schneider SBD600RCRL	X	98-0%	85-0%	75-0%	91-0%	93-15%	100-12%	100-14%

Dimmerkompatibilitätsliste

Leuchtmittel (LO-FROAGL-5WD, LO-FROAGL-7WD, LO-FROAGL-9WD, LO-FROAGL-12WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-FROAGL-5WD		LO-FROAGL-7WD		LO-FROAGL-9WD		LO-FROAGL-12WD	
	Spalte1	Spalte2	Spalte1	Spalte2	Spalte1	Spalte2	Spalte1	Spalte2
Schneider SBD630RC	95-0%	92-0%	X	X	93-19%	88-13%	99-29%	100-24%
Schneider 600RL	92-0%	91-0%	79-0%	78-0%	90-0%	91-8%	100-12%	100-11%
Schneider SBD420RCRL	89-0%	98-0%	88-0%	X	96-5%	93-5%	100-10%	100-9%
Schneider 5170	65-0%	85-0%	89-0%	X	85-15%	X	91-34%	88-31%
Schneider SBD400RL	63-0%	83-0%	69-0%	75-0%	91-0%	94-0%	100-0%	100-0%
Schneider SBDSPL	58-0%	82-0%	67-0%	78-0%	83-0%	86-0%	88-0%	99-0%
Schneider ATTD1000RL	96-0%	91-0%	90-0%	99-0%	99-0%	98-0%	100-101%	100-101%
Shuttle SDIM-T-LED-500W T & LED-T	86-0%	92-0%	89-0%	99-0%	94-2%	93-3%	98-12%	96-13%
Siemens 5TC8 284 T	X	X	64-0%	58-0%	75-14%	61-3%	99-15%	98-11%
Siemens 5WG1-528-1AB31 KNX-U	85-0%	85-0%	X	X	X	X	X	X
theben DIMAX 544 plus P T	93-0%	95-0%	X	X	X	X	100-23%	100-22%
theben DIMAX 534 plus T	100-0%	100-0%	90-0%	99-0%	97-6%	97-0%	97-2%	97-4%
Vadsbo LD220 U	83-0%	89-0%	90-0%	99-0%	99-0%	X	X	X

Dimmerkompatibilitätsliste

Leuchtmittel (LO-FROAGL-5WD, LO-FROAGL-7WD, LO-FROAGL-9WD, LO-FROAGL-12WD)

Spalte1 ▶ dimmbar ab 1 Lampe | Spalte2 ▶ dimmbar ab 4 Lampen

Dimmer	LO-FROAGL-5WD		LO-FROAGL-7WD		LO-FROAGL-9WD		LO-FROAGL-12WD	
Vari Light HQ3W	95-0%	91-0%	92-1%	99-1%	83-18%	X	98-8%	X
Vari Light JQP401W T	97-0%	99-0%	X	X	X	X	99-9%	100-9%
Vimar 20135 U	58-0%	74-0%	94-0%	100-0%	94-2%	92-2%	100-9%	99-9%
Zano WH401 L	X	99-0%	X	X	X	X	99-0%	100-0%
Zano WH251	85-0%	97-0%	X	98-0%	65-0%	94-0%	100-0%	100-0%
Zano Z GRID 600 T	X	X	87-0%	98-0%	93-0%	97-0%	X	X
Zano Z GRID 500	X	98-0%	81-0%	96-0%	74-0%	96-0%	99-0%	100-0%